# Specification

Wireless Rechargeable Multi-use Light (Version 5.0)



#### 1/7. Features:

Multi-Function: 6 Light modes: Low/Medium/High/Warning/Amber/Flashlight. (NEW: Warning is RED+Blue lights)
Health and Safety: IP65 Waterptoof, safe voltage & current; No Flicker/Glare/UV.

**4. Durable:** Use high quality LED Chips, Li-ion battery, strong Aviation Aluminum and PC Cover to ensure a long life span.

# 2/7. Applications:

Work, Car Repair, Mechanic, Camping, Power Bank, Emergency/Warning/S.O.S., Garage/Basement, Reading & Studying etc,

#### 3/7. How To Use:

1. Low/Medium/High/Warning/Amber: Short press the On/Off button to switch the light into Low/Medium/High/Warning/Amber mode.

**2. Flashlight:** Long press the On/Off button **3** seconds to switch the light into **Flashlight**.

3. Charging: Blue breath is Charging, Blue still is full.

#### 4/7. Specifications(Experiment Data):

-, /. Specifications(Experiment Data).											
Model	Size (mm)	Battery Capacity (mAh)	Power (W)	IP Level	Run Time & Lumen (High)	Run Time & Lumen (Medium)	Run Time & Lumen (Low)	Warning (Hrs) (RED+Blue)	<mark>Amber</mark> (Hrs)	Flashlight (Hrs)	Power Bank Out-put
RL-25	L150*H35 (5.9")	2500; 3.7V	1.5	IP65	/	5Hrs/120lm	80Hrs/20lm	40	5	5	DC5V 1.2A
RL-40	L242*H35 (9.5")	4000; 3.7V	2	IP65	6Hrs/200lm	12Hrs/160lm	80Hrs/30lm	50	6	6	DC5V 2.4A
RL-60	L292*H35 (11.5")	6000; 3.7V	3	IP65	6Hrs/300lm	12Hrs/200lm	100Hrs/55lm	90	6	9	DC5V 2.4A

## 5/7. Warning:

1. Charging: Please use standard Type-C 5V 1A/2A USB Charger.

2. Keep the light away from Fire, High Temperature or Extreme Environment; Do not exposure the light under the Sun.

3. Do not disassemble the light without authorization.

4. Do not shake, beat, hit or tread on the light.

## 6/7. Warranty:

- 1. 12 months limited warranty is provided. (Due to product quality problems caused by damage)
- 2. Damage to the light due to improper use and damage to the surface of the light is not covered by the warranty.
- 3. Disassemble the light without authorization is not covered by warranty.
- 4. The second damage caused by improper packing to the factory to repair or replacement is not covered by the warranty.

## 7/7. Work Style(4) & Work Mode(6):

